

Product: M4-S-AC/DC 300W



Power supply for MACH4002 switch chassis

Product Description Power supply for MACH4002 switch chassis

Technical Specifications

Product description

Description:	Power supply for MACH4002 switch chassis			
Part Number:	943870001			
More Interfaces				
Voltage input:	Non-heating appliance socket			
Power requirements				
Current consumption:	1.8 A (230 V), 4.2 A (115V)			
Input frequency:	47-63 Hz			
Nominal power of voltage supply:	350 W (230 V), 370 W (110 V)			
Operating Voltage:	100-240 V AC			
Activation Current:	typ. 40 A at 265 V AC and cold start			
Software				
Diagnostics:	LEDs (P1) at basic device			
Ambient conditions				
Ambient conditions Operating temperature:	0-+60 °C			
	0-+60 °C			
Operating temperature:	0-+60 °C Plug-in device			
Operating temperature: Mechanical construction				
Operating temperature: Mechanical construction Mounting:				
Operating temperature: Mechanical construction Mounting: Approvals	Plug-in device			
Operating temperature: Mechanical construction Mounting: Approvals Safety of industrial control equipment:	Plug-in device			
Operating temperature: Mechanical construction Mounting: Approvals Safety of industrial control equipment: Safety of information technology equipment:	Plug-in device cUL 508 cUL 60950-1 Germanischer Lloyd			

Furt	her l	nst	ruc	tions

Product Documentation:	https://www.doc.hirschmann.com
Certificates:	https://www.doc.hirschmann.com/certificates.html

Variants

Item # 943870001 Update and Revision:

© 2021 Belden, Inc

All Rights Reserved.

Although Belden makes every reasonable effort to ensure their accuracy at the time of this publication, information and specifications described here in are subject to error or omission and to change without notice, and the listing of such information and specifications does not ensure product availability.

Belden provides the information and specifications herein on an "ASIS" basis, with no representations or warranties, whether express, statutory or implied. In no event will Belden be liable for any damages (including consequential, indirect, incidental, special, punitive, or exemplary damages) whatsoever, even if Belden has been advised of the possibility of such damages, whether in an action under contract, negligence or any other theory, arising out of or in connection with the use, or inability to use, the information or specifications described herein.

All sales of Belden products are subject to Belden's standard terms and conditions of sale.

Belden believes this product to be in compliance with all applicable environmental programs as listed in the data sheet. The information provided is correct to the best of Belden's knowledge, information and belief at the date of its publication. This information is designed only as a general guide for the safe handling, storage, and any other operation of the product itself or the one that it becomes a part of. The Product Disclosure is not to be considered a warranty or quality specification. Regulatory information is for guidance purposes only. Product users are responsible for determining the applicability of legislation and regulations based on their individual usage of the product.